

RE-RP Series Repeater Panel



Product Overview

RE-RP Series is a microprocessor based repeater panel which is compatible for RE-2554 / RE-2558 Fire Alarm Control Panel. This repeater has full indication and can monitor the main FACP. This repeater is connected to RE-2554/RE-2558 FACP using RS-485 communication. Any fault / fire occurred in main fire alarm control panel is indicated in this repeater panel. The display parameters can be selected individually to suit the requirement of each remote area.

Features:

- 20 X 4 Dot Matrix LCD display.
- Alphanumeric keypads.
- RS-485 Communication for Network Repeater.
- System ON, AC ON, Battery ON, Charger ON indications.
- Drill test / Evacuate facility.
- Lamp test facility.
- Maximum 16 Mainpanels includes repeaters can be connected in a Single Network through RS-485.

Electrical Specification

Primary Power

120-220 VAC, 60/ 50 W

Battery (Lead Acid only)

Charging Current: Constant Voltage 28V @ 0.5A (Max.).
24V DC (2 Nos of 12V, 7Ah (Max.) Sealed Lead acid battery)
System Quiescent Current: 70mA

Operating Condition

Operating Temperature : 0 - 49° C / 32-120° F.
Storage Temperature : 0 - 60° C
Relative Humidity : 93 ± 2% RH (non-condensing) at 32 ± 2° C / 90 ± 3° F.

Notification Appliance Circuits (Sounder Circuit)

Operating Nominal Voltage : 24V DC
Sounder (NAC) output : 0.5A
End-Of-Line Resistor : 4.7K, 1/4 Watt

Potential Free Relay Contact


Type : Form C
No of Relays : 1
Relay Contact Rating : 2 Amps @ 30 VDC,
0.5 Amps @ 125 VAC.



Special Features:

- Ravel Indian Manufacturer, International standard.
- Operates on RS-485 communication.
- Repeats all the parameters of the main FACP.


Mounting Detail:



Mechanical Specification:

Dimensions	: (350W X 300H X 100D)
Color	: White
Construction	: 18 Gauge (1.22mm) CRCA sheet with powder-coated Finish
IP Rating	: IP50
Cable Entry	: 11x ϕ 19mm Knockout in top of the cabinet

Connection Diagram:



Note:- Maximum distance for RS 485 communication : 1 Km
Recommended cable : CAT5E or Equivalent.

Compatible Devices:

MODELS	DESCRIPTION
RE-2554 / 58	4 / 8 Zone Fire Alarm Panel

Ordering Information:

MODELS	ZONES
RE- 008RP	Up to 8 Zones
RE- 064RP	Up to 64 Zones
RE-128RP	Up to 128 Zones

India:

RAVEL ELECTRONICS PVT LTD.,
(An ISO 9001 Certified Company)
150A, Electronics Industrial Estate, Perungudi, Chennai - 96 .India.
E-Mail: marketing@ravelfire.com; Web : www.ravelfire.com

United Kingdom:

RAVEL ELECTRONICS LTD.,
Unit 11, Chancel Industrial Estate, Newhall street,
Willenhall WV13 1NX, West Midlands, United Kingdom.
E-mail: info@ravelfire.co.uk ;Web: www.ravelfire.co.uk